

NFPA No.

79

**ELECTRICAL STANDARD FOR
METALWORKING
MACHINE
TOOLS
1977**



**NATIONAL FIRE PROTECTION ASSN.
LIBRARY
470 ATLANTIC AVENUE
BOSTON, MASS. 02210**

Copyright © 1977

All Rights Reserved

**NATIONAL FIRE PROTECTION ASSOCIATION
470 Atlantic Avenue, Boston, MA 02210**

3M-7-77-FP
Printed in U.S.A.

Official Interpretations

The Committee responsible for this document will render official interpretations of the literal text and of the intent of the Committee when the text was adopted.

A request for an Official Interpretation shall be directed to the Chairman of the Committee concerned, at the National Fire Protection Association, 470 Atlantic Avenue, Boston, Massachusetts 02210, supplying five identical copies of a statement in which shall appear specific references to a single problem, and identifying the portion of the document (article, section, paragraph, etc.) for which the interpretation is requested. Such a request shall be on the business stationery of the requester and shall be duly signed. A request involving an actual field situation shall so state and all parties involved shall be named.

Licensing Provision — This document is copyrighted by the National Fire Protection Association (NFPA).

1. Adoption by Reference — Public authorities and others are urged to reference this document in laws, ordinances, regulations, administrative orders or similar instruments. Any deletions, additions and changes desired by the adopting authority must be noted separately. Those using this method are requested to notify the NFPA (Attention: Assistant Vice President — Standards) in writing of such use. The term "adoption by reference" means the citing of title and publishing information only.

2. Adoption by Transcription — **A.** Public authorities with law-making or rule-making powers only, upon written notice to the NFPA (Attention: Assistant Vice President — Standards), will be granted a royalty-free license to print and republish this document in whole or in part, with changes and additions, if any, noted separately, in laws, ordinances, regulations, administrative orders or similar instruments having the force of law, provided that: (1) due notice of NFPA's copyright is contained in each law and in each copy thereof; and, (2) that such printing and republication is limited to numbers sufficient to satisfy the jurisdiction's law-making or rule-making process. **B.** Public authorities with advisory functions and all others desiring permission to reproduce this document or its contents in whole or in part in any form shall consult the NFPA.

All other rights, including the right to vend, are retained by NFPA.

(For further explanation, see the Policy Concerning the Adoption, Printing and Publication of NFPA Documents which is available upon request from the NFPA.)

Statement on NFPA Procedures

This material has been developed under the published procedures of the National Fire Protection Association, which are designed to assure the appointment of technically competent Committees having balanced representation. While these procedures assure the highest degree of care, neither the National Fire Protection Association, its members, nor those participating in its activities accepts any liability resulting from compliance or noncompliance with the provisions given herein, for any restrictions imposed on materials or processes, or for the completeness of the text.

NFPA has no power or authority to police or enforce compliance with the contents of this document and any certification of products stating compliance with requirements of this document is made at the peril of the certifier.

See Inside Back Cover for Official NFPA Definitions

Electrical Standard for Metalworking Machine Tools

NFPA No. 79 — 1977

1977 Edition of No. 79

This edition of NFPA No. 79, adopted by the NFPA at its 1977 Annual Meeting in Washington, D.C., supersedes the 1974 edition.

The 1974 edition of this standard was approved by the American National Standards Institute under date of September 7, 1976 and designated ANSI C113.1-1974. The 1977 edition is being submitted for similar approval. The ANSI designation and date of approval will be printed on the front cover of copies of this edition printed after approval has been received.

Origin and Development of No. 79

This Standard was first submitted at the 1961 NFPA Annual Meeting under the title "Electrical Standard for Machine Tools" and was tentatively adopted subject to comments. It was extensively revised and resubmitted at the 1962 Annual Meeting when it was officially adopted. In 1965 a revised edition was adopted, reconfirmed in 1969, and in 1970, 1971, 1973, and 1974 revised editions were adopted.

To better coordinate its work, this Committee reports to the Association through the Correlating Committee of the National Electrical Code Committee. The primary reason is to correlate this Standard and the National Electrical Code, especially with respect to Article 670 thereof.

Committee on Electrical Metalworking Machine Tools

R. W. Seelbach, Chairman,

Underwriters Laboratories Inc., 207 East Ohio St., Chicago, IL 60611

E. J. Loeffler, Secretary,

National Machine Tool Builders' Assn., 7901 Westpark Dr., McLean, VA 22101

A. T. Bachelier, Westinghouse Electric Corp.

R. H. Butterfield, Caterpillar Tractor Co.

C. J. Hart, National Electrical Contractors Assn.

W. F. Huette, Allen-Bradley Co.

Robert D. Jordan, The Minster Machine Co.

R. J. Kasper, Industrial Risk Insurers

Roger Keith, Kaiser Aluminum and Chemical Corp.

J. E. Menzies, National Electrical Mfrs. Assn.

Sidney W. Nelson, Nelcor, Inc.

Walter C. Painter, Rockwell International

J. C. Sharp, International Brotherhood of Electrical Workers

Dale C. Walker, Square D Co.

This list represents the membership at the time the Committee was balloted on the text of this edition. Since that time, changes in the membership may have occurred.

Contents

Preface	79- 5
Chapter 100. General	79- 7
Chapter 110. Diagrams, Instructions, and Nameplates	79- 8
Chapter 120. Supply Circuit Disconnecting Means	79-10
Chapter 130. Protection	79-13
Chapter 140. Control Circuits	79-19
Chapter 150. Control Components and Equipment	79-21
Chapter 160. Control Enclosures and Compartments	79-23
Chapter 170. Location and Mounting of Control Equip- ment	79-25
Chapter 180. Operator's Control Stations and Equipment	79-27
Chapter 190. Accessories and Lighting	79-31
Chapter 200. Conductors	79-33
Chapter 210. Wiring Methods and Practices	79-37
Chapter 220. Raceways, Junction and Pull Boxes	79-40
Chapter 230. Motors and Motor Compartments	79-44
Chapter 240. Grounded Circuits and Equipment Ground- ing	79-45
Appendix A. Glossary of Terms	79-47
Appendix B. References to Other Codes and Standards	79-52

Electrical Standard for Metalworking Machine Tools

NFPA No. 79 — 1977

PREFACE

A Metalworking Machine Tool, as covered by this Standard, is defined herein as follows:

A metalworking machine tool is a power driven machine not portable by hand, used to shape or form metal by cutting, impact, pressure, electrical techniques, or a combination of these processes.

Other types of electrically powered production and processing equipment are excluded, and their electrical equipment and installations should be judged under the general provisions of the National Electrical Code (NFPA No. 70—1978) rather than this Standard.

In September 1941, the machine tool industry wrote its first Electrical Standard to make machine tools safer to operate, more productive, less costly to maintain and to improve the quality and performance of their electrical components. That particular standard served as an American "War Standard."

To study the special electrical problems involved with machine tools, the Electrical Section of the National Fire Protection Association in 1941 sanctioned a Special Subcommittee on Wiring, Overcurrent Protection and Control of Motor Operated Machine Tools. This Subcommittee, cooperating with machine tool builders, manufacturers of control equipment, and Underwriters' Laboratories, Inc., conducted tests and investigated the peculiar conditions involved with machine tools which might warrant exception to certain specific National Electrical Code requirements. This investigation resulted on August 4, 1942, in an Interim Amendment and first appeared in a 1943 Supplement to the 1940 Edition of the National Electrical Code as Article 670, Machine Tools. It remained essentially unchanged through the 1959 edition.

Meanwhile, manufacturers of other types of industrial equipment erroneously began to follow the specialized practices permitted by Article 670. Late in 1952 a Technical Subcommittee on Fundamentals of Electrically Operated Production Machinery and Material Handling and Processing Equipment for Fixed Locations was organized to attempt to group in one article the special requirements

of this broad field. The extremely broad scope introduced so many problems, that in December 1956, this Technical Subcommittee was reorganized into an NFPA Committee whose scope was limited to Machine Tools and whose objective was the preparation of this NFPA Standard with corresponding revisions in Article 670 in the National Electrical Code.

The electrical equipment of a modern industrial machine tool may vary from that found on a single motor machine such as a drill press which performs a simple, repetitive operation, to that of the very large, multimotored automatic machines which involve highly complex electrical control systems, including electronic and solid state devices and equipment. Generally these machines are especially designed, factory wired and tested by the builder, and then erected in the plant in which they will be used. Because of their importance to the production of the plant, and their usual high cost, they are customarily provided with many safeguards and other devices, not often incorporated in the usual motor and control application as contemplated by the National Electrical Code.

Although these machines may be completely automatic, they are constantly attended, when operating, by a highly skilled operator. The machine tool usually incorporates many special devices to protect the operator, protect the machine and building against fires of electrical origin, protect the machine and work in process against damage due to electrical failures, and protect against loss of production due to failure of a machine component. To provide these safeguards, it may be preferable to sacrifice deliberately a motor or some other component, rather than to chance injury to the operator, the work, or the machine. It is because of such considerations that this standard varies from the basic concepts of motor protection as contained in the National Electrical Code.

CHAPTER 100. GENERAL

100-1. Purpose.

(a) The purpose of this Electric Standard is to provide detailed information for the application to machine tools of electrical apparatus which will promote safety to life and property.

(b) This Standard is a minimum Standard and is not intended to limit or inhibit the advancement of the state of the art.

100-3. Scope.

(a) The provisions of this Standard apply to all electric/electronic equipment, apparatus, systems, and wiring of an industrial machine tool, commencing at the place of connection of the supply to the machine tool electrical equipment.

(b) The provisions of this Standard apply to electric equipment for use on circuits which operate from a supply voltage of 600 volts or less.

(c) This Standard shall not be considered adequate for machine tools intended for use in areas defined as hazardous locations by the National Electrical Code (NFPA No. 70 — 1978).

(d) This Standard is not intended to apply to:

(1) Fixed or portable tools judged under the requirements of a testing laboratory acceptable to the authority having jurisdiction.

(2) Tools on which the motor or motors total two horsepower or less.

(e) The installation of the machine tool is covered by Article 670 of the National Electrical Code (NFPA No. 70 — 1978).

100-5. Definition of Metalworking Machine Tools. For the purpose of this Standard, a machine tool is defined as follows:

A power driven machine not portable by hand, used to shape or form metal by cutting, impact, pressure, electrical techniques, or a combination of these processes.

100-6. Other Definitions. For purposes of this Standard, definitions of some other terms are given in Appendix A.

100-9. Other Standards. Other organizations having standards which may provide additional information are listed in Appendix B.

100-11. Nominal Voltages. All voltages mentioned in this Standard are nominal.

CHAPTER 110. DIAGRAMS, INSTRUCTIONS, AND NAMEPLATES

110-1. Diagrams. Diagrams showing all of the electric circuits on the machine tool shall be provided.

110-3. Instructions. Information referring to the installation, operation, and maintenance of the equipment shall be furnished.

110-4. Markings. Nameplates, marking, and identification plates shall be of sufficient durability to withstand the environment involved.

110-5. Equipment Nameplates.

(a) A nameplate listing supply voltage, phase, frequency, full-load current, ampere rating of largest motor, short-circuit interrupting capacity of the machine overcurrent protective device if furnished, and diagram number shall be attached to the control equipment enclosure or machine where plainly visible after installation.

The full-load current shown on the nameplate shall not be less than the sum of the full-load currents required for all motors and other equipment which may be in operation at the same time under normal conditions of use. Where unusual type loads, duty cycles, etc., require oversized conductors, the required capacity shall be included in the marked "full load current."

Where more than one incoming supply circuit is to be provided, the nameplate shall state the above information for each circuit.

(b) Where overcurrent protection is provided in accordance with Section 130-3, the machine tool shall be marked "Overcurrent protection provided at machine supply terminals."

110-7. Machine Marking. The machine tool shall be marked with the builder's name, trademark, or other identification symbol.

110-8. Warning Marking. A warning marking shall be provided adjacent to the disconnect operating handle(s) if the disconnect(s) that are interlocked with the enclosure door do not de-energize all exposed live parts when the disconnect(s) are in the "off" position.

110-9. Component Marking.

(a) Where electrical equipment is removed from its original enclosure or where equipment is so placed that the manufacturer's identification plate is not easily read, an additional identification plate shall be attached to the machine tool or enclosure.

(b) Where the motor nameplate or the connection diagram plate is not visible, an additional plate shall be provided where it can be easily read.

(c) Nameplates or identification plates shall not be removed from electrical equipment.

110-11. Device Identification.

(a) All control panel devices shall be plainly identified with the same designation as shown on the diagrams.

Exception No. 1. Where the size or location of the devices makes individual identification impractical, group identification shall be used.

Exception No. 2. Tools on which the electrical equipment consists only of a single motor, motor-controller, pushbutton stations, and work lights.

(b) All devices external to the control panel shall be identified by a nameplate with the same designation as shown on the diagrams, and mounted adjacent to (not on) the device.

Exception: Devices covered by Section 110-13.

110-13. Function Identification. Each control station device (push-button, indicating light, selector switch, etc.) shall be identified as to its function by a legend plate.

CHAPTER 120. SUPPLY CIRCUIT DISCONNECTING MEANS

120-1. General Requirements. A disconnecting means shall be provided for each incoming supply circuit.

120-2. Type. The disconnecting means shall be manually operable and shall be a fusible or nonfusible motor circuit switch, a circuit breaker, or a circuit interrupter.

120-3. Rating.

(a) The ampacity of the disconnecting means shall not be less than 115 per cent of the sum of the full-load currents required for all equipment which may be in operation at the same time under normal conditions of use.

(b) The interrupting capacity of the disconnecting means shall not be less than the sum of the locked-rotor current of the largest motor plus the full-load current of all other connected operating equipment.

(c) Fusible motor-circuit switches or circuit breakers shall be applied in accordance with Chapter 130.

120-5. Position Indication. The disconnecting means shall plainly indicate whether it is in the open or closed position.

120-7. Supply Conductors To Be Disconnected. Each disconnecting means shall disconnect all ungrounded conductors of a single supply circuit simultaneously. Where there is more than one source, additional individual disconnecting means shall be provided for each supply circuit, so that all supply to the machine may be interrupted.

120-9. Connections To Supply Lines. Incoming supply line conductors shall terminate at the disconnecting means with no connection to terminal blocks or other devices ahead of the disconnecting means.

120-11. Exposed Live Parts. With the disconnecting means open, there shall be no exposed live parts.

Exception: As permitted in Section 160-13.

120-13. Mounting.

(a) The disconnecting means shall be mounted within the control enclosure or adjacent thereto. Where mounted within the control enclosure, the disconnecting means shall be mounted at

the top of the control panel with no other equipment mounted directly above it.

(b) Where two or more disconnecting means are provided within the control enclosure for multiple supply circuits, they shall be grouped in one location.

120-15. Interlocking. Each disconnecting means shall be mechanically or electrically interlocked, or both, with the control enclosure doors.

Exception: A disconnecting means used only for maintenance lighting circuits within control enclosures shall not be required to be interlocked with the control enclosure doors.

120-17. Operating Handle.

(a) The operating handle of the disconnecting means shall be readily accessible.








































(b) The center of the grip of the operating handle of the disconnecting means, when in its highest position, shall not be more than $6\frac{1}{2}$ feet above the floor. A permanent operating platform, readily accessible by means of a permanent stair or ladder, shall be considered as the floor for the purpose of this requirement.

(c) The operating handle shall be capable of being locked only in the "off" position.

(d) When the control enclosure door is closed, the operating handle shall positively indicate whether the disconnecting means is in the open or closed position.

DIAGRAM 130-1 — Protection of Machine Tool Electrical Circuits

TYPICAL DIAGRAMS — PROTECTION OF MACHINE TOOL ELECTRICAL CIRCUITS

LINE	REFERENCE	SINGLE MTR.	MULTI MOTOR			
A	SUPPLY N. E. CODE, ARTICLE 670					
B	DISCONNECTING MEANS CHAPTER 120					
C	OVERCURRENT PROTECTION (WHEN SUPPLIED) SECTION 130-3					
D	ADDITIONAL OVERCURRENT PROTECTION (AS REQUIRED) SECTION 130-5					
E	CONTROL CIRCUITS CONDUCTORS SECT. 130-15 TRANSFORMER SECT. 130-19 UNDERVOLTAGE SECT. 130-21					
F	MOTOR CONTROLLERS SECTION 130-7					
G	MOTOR OVERLOAD SECTION 130-11					
H	MOTORS CHAPTER 230 SPECIAL MOTOR OVERLOAD SECTION 130-13					
	ALL CONDUCTORS CHAPTER 200	FIG I	FIG II	FIG III	FIG IV	

CHAPTER 130. PROTECTION

130-1. Machine Tool Circuits. Diagram 130-1 shows typical circuits which are acceptable for protection of machine tool motors and controls. Protective interlocks are not shown.

130-3. Supply Conductor and Machine Overcurrent Protection. The overcurrent protection as shown in line C of Diagram 130-1, Figures I through IV inclusive, may or may not be furnished as part of the machine tool. Where furnished as a part of the machine tool it shall consist of a single circuit breaker or set of fuses and the machine shall bear the marking required in Section 110-5.

130-5. Additional Overcurrent Protection. The additional overcurrent protection shown in line D of the Diagram 130-1, Figures III and IV, shall be provided as part of the machine control. Such overcurrent protection (fuse or overcurrent trip unit of a circuit breaker) shall be placed in each ungrounded branch circuit conductor. A circuit breaker shall open all ungrounded conductors of the branch circuit.

130-7. Location of Protective Devices. Overcurrent protective devices shall be located at the point where the conductor to be protected receives its supply.

Exception No. 1. Where all of the following conditions are complied with, (1) the conductor has an ampacity of at least one-third that of the conductor from which it is supplied, and (2) it is suitably protected from physical damage, and (3) is not over 25 feet long, and (4) terminates in a single circuit breaker or set of fuses.

Exception No. 2. Where all of the following conditions are complied with, (1) the conductor has an ampacity of not less than the sum of the maximum continuous load currents supplied, and (2) is not over 10 feet long, and (3) does not extend beyond the control panel enclosure.

130-9. Motor Branch Circuits.

(a) The overcurrent protective device for a branch circuit supplying a single motor shall be capable of carrying the starting current of the motor. Overcurrent protection shall be considered as being obtained when the overcurrent device has a rating or setting not exceeding the values given in Table 130-A. Where the overcurrent protection specified in the Table is not sufficient for the starting current of the motor, it may be increased to a maximum of 400 percent of the motor full-load current for inverse time circuit

Table 130-A
Maximum Rating or Setting
of Motor Branch Circuit Protective Devices
for Various Types of Motors

TYPE OF MOTOR	Per Cent of Full-Load Current		
	Fuse Rating		Inverse Time Circuit Breaker Rating
	Time Delay or Dual Element	Nontime Delay	
MOTORS MARKED WITH CODE LETTER INDICATING LOCKED-ROTOR KVA			
All A.C. Single-Phase and Polyphase Squirrel- Cage and Synchronous Motors.			
Code Letter A	125	150	150
Code Letter B to E	125	250	200
Code Letter F to V	125	300	250
MOTORS NOT MARKED WITH CODE LETTER INDICATING LOCKED-ROTOR KVA			
Single-Phase, All Types	125	300	250
Squirrel-Cage and Syn- chronous	125	300	250
High Reactance Squir- rel Cage:			
Not more than 30 Amp. Full-Load Current	125	250	250
More than 30 Amp. Full-Load Current	125	200	200
Wound Rotor	125	150	150
Direct Current	125	150	150

breakers and nontime delay fuses, and a maximum of 225 percent for time delay or dual element fuses.

(b) Two or more motors and their control equipment may be connected to a single branch circuit provided all of the following conditions are complied with:

(1) The maximum size of a conductor (selected from Table 200-B) connected to a motor controller shall not exceed the values given in Table 130-B.

(2) The rating or setting of the overcurrent protective device shall be as low as practicable, and shall not exceed the values in Table 130-C for the smallest conductor in the circuit.

(3) The motor and controller circuits shall be so arranged that a minimum number of branch-circuit overcurrent protective devices are used.

130-11. Motor Overload.

(a) Overload devices shall be provided to protect each motor, motor controller, and branch-circuit conductors against excessive heating due to motor overloads or failure to start.

(b) Resetting of the overload device shall not restart the motor.

(c) The minimum number and location of running overcurrent units shall be determined from Table 130-D.

Table 130-B
Maximum Conductor Size for Given
Motor Controller Size*

Motor Controller Size	Maximum Conductor Size, AWG or MCM
0	10
1	8
2	4
3	0
4	000
5	500

*See ANSI C19.3 — 1973, Table 8.

Table 130-C

**Relationship Between Conductor Size and
Maximum Rating or Setting of Short Circuit
Protective Device for Power Circuits**

Conductor Size AWG	Max. Rating Non-Time Delay Fuse or Inverse Time Circuit Breaker	Time Delay or Dual Element Fuse
14	60	30
12	80	40
10	100	50
8	150	80
6	200	100
4	250	125
3	300	150
2	350	175
1	400	200
0	500	250
00	600	300
000	700	350
0000	800	400

Table 130-D

Running Overcurrent Units

Kind of Motor	Supply System	Number and Location of Overcurrent Units (such as trip coils, relays, or thermal cutouts.)
1-phase A.C. or D.C.	2-wire, 1-phase A.C. or D.C. ungrounded	1 in either conductor
1-phase A.C. or D.C.	2-wire, 1-phase A.C. or D.C., one conductor grounded	1 in ungrounded conductor
1-phase A.C. or D.C.	3-wire, 1-phase A.C. or D.C., grounded-neutral	1 in either ungrounded conductor
3-phase A.C.	Any 3-phase	*3, one in each phase

*Exception: Unless protected by other approved means.

NOTE: For 2-phase power supply systems see the National Electrical Code, Section 430-37.

Table 130-E
Relationship Between Conductor Size and Overcurrent
Protection Rating for Control Circuits

Conductor Size, AWG	Max. Rating of Overcurrent Protective Device, Amp.
22-30	6
20	10
18	15
16	30
14	45
12	60
10	70

130-13. Motor Overload, Special-Duty. Short-time rated motors or high-reversing duty motors which cannot be adequately protected by external overload devices shall be protected by a thermal device mounted in the motor and sensitive to the temperature of the motor, or to both motor temperature and current.

130-15. Control Circuit Conductors.

(a) The conductors in the control transformer secondary circuit shall be protected against overloads and short circuits. A branch-circuit overcurrent device (fuse or circuit breaker) shall be connected in series with each branch control circuit. Where the circuit is grounded, the protective device shall be located only in the ungrounded side.

(b) The rating or setting of the overcurrent protective device shall be as low as practicable, and shall not exceed the values in Table 130-E for the smallest conductor in the circuit.

130-17. Lighting Branch Circuits. Overcurrent protection for lighting branch circuits shall not exceed 15 amperes.

130-19. Control Circuit Transformer.

(a) The control circuit transformer shall be protected in the secondary circuit against overloads and short circuits. Where the

circuit is grounded, the protective device(s) shall be located only in the ungrounded side.

(b) Where multiple overcurrent protective devices are used to protect individual branch circuits, and the sum of the current ratings of these overload protective devices exceeds the current allowed in Table 130-F, a single overload protective device complying with Table 130-F shall be placed in the circuit ahead of the multiple protective devices. The rating or setting of the overcurrent protective device shall not exceed the values in Table 130-F for the rating of the control transformer.

130-20. Common Overcurrent Device. The use of the same overcurrent device to provide the protection called for in Sections 130-15, 130-17, and 130-19 shall be permitted.

130-21. Undervoltage. Undervoltage protection shall be provided for all equipment which creates an unsafe condition should a motion be initiated upon the return of power after an undervoltage condition.

Table 130-F
Control Transformer Overcurrent Protection
(115 Volt Secondary)

Control Transformer Size, Volt-Amperes	Maximum Rating, Amperes
50	0.5
100	1.0
150	1.6
200	2.0
250	2.5
300	3.2
500	5
750	8
1000	10
1250	12
1500	15
2000	20
3000	30
5000	50

NOTE: For transformers larger than 5000 volt-amperes, the protective device rating shall be based on 125 percent of the secondary current rating of the transformer.

CHAPTER 140. CONTROL CIRCUITS

140-1. Source of Control Power. The source of supply for all control circuits shall be taken from the load side of the main disconnecting means.

140-3. Control Circuit Voltages.

(a) Alternating-current (AC) control voltage shall be 115 volts or less, single phase, obtained from a transformer with an isolated secondary winding.

Exception No. 1. Other voltages shall be permitted, where necessary, for the operation of electronic, precision, static, or similar devices used in the control circuit.

Exception No. 2. Exposed, grounded control circuits shall be permitted when supplied by a transformer having a primary rating of not more than 115 volts, a secondary rating of not more than 25 volts, and a capacity of not more than 50 volt-amperes.

Exception No. 3. Any electro-mechanical magnetic device having an inrush current exceeding 20 amperes at 115 volts shall be permitted to be energized at line voltage through relay contacts. The relay coil shall be connected to the control circuit.

(b) Direct-current (DC) control voltage shall be 250 volts or less.

Exception. Other voltages shall be permitted to be used, where necessary, for the operation of electronic, precision, static, or similar devices used in the control circuit.

140-4. Grounding of Control Circuits. Grounded or ungrounded control circuits shall be permitted as provided for in Section 240-1.

140-5. Connection of Control Devices. All operating coils of electro-mechanical magnetic devices and indicator lamps (or transformer primary windings for indicator lamps) shall be directly connected to the same side of the control circuit. All control circuit contacts shall be connected between the coil and the other side of the control circuit.

Exception No. 1. Electrical interlock contacts on multi-speed motor controllers where the wiring to these contacts does not extend beyond the control enclosure.

Exception No. 2. Overload relay contacts where the wiring to these contacts does not extend beyond the control enclosure.

Exception No. 3. Contacts of multi-pole control circuit switching devices that simultaneously open both sides of the control circuit.

Exception No. 4. Ground test switching device contacts in ungrounded control circuits.

Exception No. 5. Solenoid test switching device contacts in ungrounded circuits.

Exception No. 6: Coils or contacts used in electronic control circuits where the wiring to these coils or contacts does not extend beyond the control enclosure.

Exception No. 7. "Run" pushbuttons for two-hand operation, such as for presses having ground detection circuits and overcurrent protection in each conductor.

140-7. Jog Circuits. Jog circuits, where used, shall be designed to prevent continuous run or automatic operation.

CHAPTER 150. CONTROL COMPONENTS AND EQUIPMENT

150-3. Connections. Means for making conductor connections shall be provided on or adjacent to all control devices mounted in the control enclosure.

150-5. Subpanels. Subpanels with concealed or inaccessible internal wiring or components shall be mounted and wired so as to be removable.

150-7. Manual and Electro-Mechanical Motor Controllers.

(a) Each motor controller shall be capable of starting and stopping the motor or motors which it controls, and for alternating current motors shall be capable of interrupting the stalled rotor current of the motor or motors.

A controller rated in horsepower shall be used for a $\frac{1}{8}$ horsepower or larger motor.

(b) Alternating current motor controllers shall open all of the supply conductors leading to associated motors.

Table 150-A
Horsepower Ratings for Special Duty Motor
Controller Applications*

Size of Motor Controller	Three Phase Horsepower at		
	200 Volts	230 Volts	460/575 Volts
0	1½	1½	2
1	3	3	5
2	7½	10	15
3	15	20	30
4	25	30	60
5	60	75	150
6	125	150	300

*See ANSI C19.7-1973, Table 4.

(c) Where machine operation requires a motor controller to repeatedly open high motor current, such as in plug-stop, plug-reverse, or jogging (inching) duty, requiring continuous operation with more than five openings per minute, the controller shall be derated in accordance with Table 150-A.

(d) Several motors shall be permitted to be operated from one motor controller where separate overload protection is provided for each motor, and the horsepower rating of the controller is not exceeded.

150-9. Marking on Motor Controllers. A controller for a motor rated $\frac{1}{8}$ horsepower or more shall be marked with the voltage, phase, horsepower rating, and such other data as may be needed to properly indicate the motor for which it is suitable.

CHAPTER 160. CONTROL ENCLOSURES AND COMPARTMENTS

160-1. Type. Enclosures and compartments shall be nonventilated and constructed to exclude such materials as dust, flyings, oil, and coolant.

Exception: Equipment requiring ventilation shall be permitted to be:

(a) *housed in a separate ventilated portion of the enclosure or compartment, or*

(b) *housed in a separate ventilated enclosure or compartment.*

160-2. Nonmetallic Enclosures. Nonmetallic enclosures approved for the purpose shall be permitted. For grounding provisions see Section 240-5.

160-3. Compartment Location. Compartments for built-in control shall be completely isolated from coolant and oil reservoirs. The compartment shall be readily accessible and completely enclosed; it shall not be considered enclosed where it is open to the floor, the foundation upon which the machine tool rests, or to other compartments of the machine tool which are not clean and dry.

160-5. Wall Thickness. The walls of compartments shall not be less than the following: No. 14 MSG gage for sheet steel; $\frac{1}{8}$ inch for cast metal; or $\frac{3}{32}$ inch for malleable iron.

160-7. Dimensions. The depth of the enclosure or compartment including doors shall not be less than the maximum depth of the enclosed equipment plus the required electrical clearances.

160-9. Doors. All enclosures or compartments shall have hinged doors which swing about a vertical axis and shall be held closed with captive fasteners or vault-type hardware. The thickness of metallic doors shall not be less than that indicated in Section 160-5. The width of doors shall not exceed 36 inches.

160-11. Gaskets. Where gaskets are used they shall be of an oil-resistant material and shall be securely attached to the door or enclosure.

160-13. Interlocks. All door(s) which permit access to live parts operating at 50 volts or more shall be so interlocked that the door(s) cannot be opened unless all power is disconnected.

Exception No. 1. External interlocking circuits operating at less than 150 volts need not be disconnected provided that the circuit conductors are identified with a yellow colored insulation as described in Section 210-1 (a) and a warning marking is attached to the door in accordance with Section 110-8.

Exception No. 2. It shall be permitted to provide means for qualified persons to gain access without removing power. The interlocking shall be reactivated automatically when the door(s) is closed.

CHAPTER 170. LOCATION AND MOUNTING OF CONTROL EQUIPMENT

170-1. General Requirements.

(a) Control equipment shall be so mounted and located that it will not interfere with machine adjustments or maintenance.

(b) Pipe lines, tubing, or devices for handling air, gases, or liquids shall not be located in enclosures or compartments containing electrical control equipment.

Exception: Equipment for cooling electronic devices.

170-3. Control Panels.

(a) All devices mounted on the control panel and connected to supply circuit voltage, or to both supply and control circuit voltages, shall be grouped above or to the side of devices connected only to control voltages.

Exception: Where supply circuit voltage is 150 volts or less.

(b) The panel shall not be set to such depth from door frame or other projecting portion of machine as to interfere with inspection and servicing.

170-5. Control Panel Enclosure. The enclosure shall be mounted in such a manner and position as to guard it against oil, dirt, coolant, and dust, and to minimize the possibility of damage from floor trucks or other moving equipment.

170-7. Clearance in Enclosures.

(a) Enclosures or compartments for mounting control panels shall provide adequate space between panel and case for wiring and maintenance.

(b) Exposed, nonarcing, bare, live parts within an enclosure or compartment shall have an air space between them and the uninsulated walls of the enclosure or compartment, including conduit fittings, of not less than $\frac{1}{2}$ inch. Where barriers between metal enclosures or compartments and arcing parts are required, they shall be of flame-retardant insulating materials.

170-9. Machine Mounted Components.

(a) Control equipment such as limit switches, brakes, solenoids, position sensors, etc., shall be mounted rigidly in a readily accessible and reasonably dry and clean location, and shall be free from possibility of accidental operation by normal movement of machine components or operator. Such equipment shall be mounted with sufficient clearance from surrounding surfaces to make its removal and replacement easy.

(b) All limit switches or position sensors shall be so installed that accidental overtravel by the machine will not damage the limit switch or sensor.

(c) Solenoids shall be accessible and shall not be submerged in oil.

Exception: Where the solenoid is sealed in an individual oil-filled container.

CHAPTER 180. OPERATOR'S CONTROL STATIONS AND EQUIPMENT

180-1. Pushbuttons, Selector Switches, Indicating Lights.

(a) All pushbutton and selector switch operators and indicating lights shall be of the oiltight type.

(b) Pushbutton operators shall be color coded in accordance with Table 180-1.

Exception: "Stop" function operators of the wobblestick or rod-operated types in the bottom of a pendant station need not be colored red.

(c) Emergency pushbutton operators shall be of the palm or mushroom type.

(d) Pushbutton operators used to initiate a "stop" function shall be of the extended operator or mushroom head types.

(e) Pushbutton operators used to initiate a "start" function or movement of machine elements (slides, spindles, carriers, etc.) shall be constructed or mounted so as to minimize inadvertent operation.

Exception: Mushroom-type operators shall be permitted to initiate "start" functions where installed in accordance with Section 180-5.

(f) Indicating (pilot) light lenses shall be color coded in accordance with Table 180-2.

(g) Illuminated operator lenses shall be color coded in accordance with Tables 180-1 and 180-2, as applicable.

180-3. Emergency Stop Controls.

(a) All machines shall incorporate one or more emergency stop controls which, upon momentary operation, shall stop all machine motions and, when actuated, shall not create other hazards.

(b) All machine motions stopped by the emergency or master stop shall be restartable only by deliberate action by the operator.

(c) Emergency stop controls shall be located at each operator control station and at other operating stations where emergency shutdown may be needed.

(d) Stop controls shall be continuously operable from all operating stations.

Table 180-1
Pushbutton Color Code

Color	Typical Function	Example
Red	Stop, Emergency Stop, Off	Stop of one or more motors; master stop; emergency stop.
Yellow	Return, Emergency Return	Return of machine elements to safe position.
Green or Black	Start, On	Start of a cycle or a partial sequence; inching, jogging; start of one or more motors.
White, Gray or Light Blue	Any function not covered by the above colors	

Table 180-2
Indicating (Pilot) Light Lens Color Code

Color	Typical Function	Example
Red	Danger, Abnormal Condition, Fault Condition	Faults in air, water, lubricating or filtering systems; Excess pressure or temperature; Indication that a protective device has stopped the machine (because of an overload, overtravel or other failure).
Amber or Yellow	Attention. Caution. Marginal Condition	Automatic cycle running; some value (current, temperature) is approaching its permissible limit; ground-fault indication.
Green	Machine ready	Machine ready for operation; all necessary auxiliaries functioning, units in starting position and hydraulic pressure or output voltage of a motor-generator in the specified range, etc. Cycle completed and machine ready to be re-started.
White or Clear	Normal Condition	Normal pressure of air, water, lubrication.
Blue	Any significant function not covered by the above colors	

180-5. Two-Hand Control. Two-hand control, where used, shall:

(a) Be protected against unintentional operation.

(b) Have the pushbutton contacts connected in series and shall be arranged by design and construction or separation, or both, to require the concurrent use of both hands to initiate the machine operation.

(c) For presses, press brakes, and shears, incorporate an anti-repeat feature.

180-7. Foot-Operated Switches.

(a) Foot-operated switches shall be protected so as to prevent accidental actuation by falling or moving objects and from unintended operation by accidental stepping onto the switch.

(b) The switch actuating pedal shall have a nonslip contact area.

180-9. Control Station Enclosures. All operator control station enclosures shall be dust, moisture, and oil tight.

180-11. Arrangement of Control Station Components. All "start" pushbuttons shall be mounted above or to the left of their associated "stop" pushbuttons.

Exception No. 1: "Start" pushbuttons in series, such as operating pushbuttons on punch presses.

Exception No. 2: Wobble-stick or rod-operated "emergency stop" pushbuttons mounted in the bottom of pendant stations.

180-13. Legend Plates. Legend plates shall be so located that they can be easily read by the machine operator.

180-15. Location of Control Stations.

(a) All stations shall be mounted in locations that will minimize exposure to oil, coolant, and other contaminates.

(b) Controls shall be within normal reach of the machine operator, and shall be so placed that he does not have to reach past spindles or other moving parts.

(c) Controls shall be located so that unintentional operation by normal movement of the machine, operator, or work will be unlikely.

(d) Pendant operator control stations shall comply with grounding and bonding requirements of Sections 240-7 and 240-9(c).

180-17. Pendant Stations.

(a) Pendant operator control station enclosures shall be oiltight.

(b) A wobble stick or rod operator at the bottom of the station shall be permitted for 'Emergency Stop' controls.

(c) Grounding and bonding shall comply with Sections 240-7 and 240-9 (c).

CHAPTER 190. ACCESSORIES AND LIGHTING

190-1. Attachment Plugs and Receptacles (External to Control Enclosure).

(a) Attachment plugs and receptacles shall be of a locking type to prevent accidental "disconnections," and approved for the voltage applied. Where used on 300 volts or over they shall be skirted and constructed to contain any arc generated when a connection is made or broken.

(b) Attachment plugs and receptacles shall be provided with a grounding pole and so constructed that the grounding pole is made before any current-carrying poles are made and is not broken until all current-carrying poles of the attachment plug have been disconnected. A grounding pole shall not be used as a current-carrying part.

(c) They shall be provided with gaskets to prevent entrance of oil or moisture when in operating position, and means shall be provided to cover the receptacle when the plug is removed.

190-2. Receptacles (Internal to Control Enclosure).

(a) Receptables internal to control enclosure shall be permitted only for maintenance equipment, and shall be of the parallel-blade grounding type rated 125 volts, 15 amperes.

(b) Receptacles shall be supplied from a 115 volt AC source and shall have individual overcurrent protection not to exceed 15 amperes.

(c) The source of power shall be the equipment control transformer, a separate isolating transformer, or the maintenance lighting circuits permitted in Sections 190-3(b)(3) and 190-3(b)(4).

(d) The receptacles shall not be accessible when the electrical equipment doors or covers are in the closed position.

190-3. Control Panel, Instrument, and Machine Work Lights.

(a) The lighting circuit voltage shall not exceed 150 volts between conductors.

(b) Lights shall be supplied from one of the following sources:

(1) A separate isolating transformer connected to the load side of the machine tool disconnecting means.

(2) A grounded 115-volt machine tool control circuit.

(3) The plant lighting circuit shall be permitted for the supply of a maintenance lighting circuit in control enclosures only.

(4) A separate isolating transformer connected to the line side of the machine tool disconnecting means shall be permitted for the supply of a maintenance lighting circuit in control enclosures only.

(c) The conductors to stationary lights used as an integral part of the machine shall be Type MTW, and the conductors within the fixtures shall not be smaller than No. 18 AWG.

(d) Flexible cords shall be Types SO, STO, SJO, or SJTO.

(e) Grounding shall comply with the provisions of Section 240-3.

(f) Incandescent lampholders shall be switchless. The fixture shall not incorporate an attachment plug receptacle.

(g) Stroboscopic effects from lights shall be avoided.

CHAPTER 200. CONDUCTORS

200-1. Power and Control.

(a) Conductors (other than those permitted in Section 200-3.) shall conform to one of the following:

(1) Machine tool wire shall be Type MTW as specified in Section 200-5.

Exception No. 1: Conductors with insulation characteristics equivalent to those given in Sections 200-5(b) and (c) and with strandings other than those specified in Table 200-A shall be permitted on individual devices purchased completely wired (i.e., motor starters, etc.)

Exception No. 2: Where subjected to temperatures exceeding the limits for Type MTW, conductors having suitable insulation shall be used.

(2) Multiconductor flexible cords, Types SO, STO, SJO, or SJTO.

(3) Special multiconductor control cables having individual conductors of a type specified in Section 200-5 and a jacket suitable for the purpose.

Exception: The marking specified in Section 200-5(d) shall be permitted on the outer surface of the jacket.

(b) Conductors shall not be smaller than:

(1) Power Circuits No. 14

(2) Lighting and control circuits on the machine and
in raceways No. 16

Exception: No. 18 shall be permitted in a jacketed, multiconductor cable assembly.

Table 200-A
Single Conductor Construction — Type MTW

Wire Size AWG MCM	Thickness of Insulation In Mils		Minimum Stranding	
	A	B	Nonflexing	Flexing
22	30	15	7	•
20	30	15	10	10 ^b
18	30	15	16	16 ^b
16	30	15	19 ^a	26 ^b
14	30	15	19 ^a	41 ^b
12	30	15	19 ^a	65 ^b
10	30	20	19 ^a	104 ^b
8	45	30	19 ^a	•
6	60	30	19 ^a	•
4-2	60	40	19 ^a	•
1-0000	80	50	37 ^a (19 ^d)	•
250-500	95	60	61 ^a (37 ^d)	•

a) ASTM designation B-8, Class C (1969).
 b) ASTM designation B-174, Class K (1964).
 c) Nonflexing construction shall be permitted for flexing service.
 d) Shall be permitted.

Table 200-B
Conductor Ampacity

Conductor Size AWG	Ampacity In		Conductor Size AWG or MCM	Ampacity In	
	Cable or Raceway	Control Enclosure		Cable or Raceway	Control Enclosure
30		0.5	00	145	225
28		0.8	000	165	260
26		1	0000	195	300
24	2	2	250	215	340
22	3	3	300	240	375
20	5	5	350	260	420
18	7	7	400	280	455
16	10	10	500	320	515
14	15	20	600	355	575
12	20	25	700	385	630
10	30	40	750	400	655
8	40	55	800	410	680
6	55	80	900	435	730
4	70	105	1000	455	780
3	80	120			
2	95	140			
1	110	165			
0	125	195			

(3) Control circuits on panels No. 18

(4) Electronic, precision, and static control See Section 200-3.

(c) The continuous current carried by conductors shall not exceed the values given in Table 200-B.

(d) Motor circuit conductors shall have an ampacity not less than 125 per cent of the full-load current rating of the highest rated motor in the group, plus the sum of the full load current ratings of all other connected motors and apparatus in the group which may be in operation at the same time.

200-3. Electronic, Precision, and Static Control.

(a) Conductors used to connect electronic, precision, static, or similar devices or panels shall be Type MTW in accordance with Table 200-A, or shall conform to the following:

(1) Conductor insulation shall be suitable for the purpose and adequate for the voltage on that conductor. Where the conductors are run with, or adjacent to, other conductors, all conductors shall be insulated for the maximum voltage involved.

(2) Conductors shall be of annealed stranded copper.

Exception: Solid conductors No. 24-30, within the control enclosure and not subject to flexing, shall be permitted.

(3) Printed circuit boards of flame-retardant material shall be permitted in place of conventional conductor assemblies.

(b) Size of conductors.

(1) Conductors in raceways shall not be smaller than No. 18.

Exception. In a jacketed, multiconductor cable assembly, No. 24 or larger conductors shall be permitted.

(2) Conductors within the control enclosures shall not be smaller than No. 26.

Exception: For short jumpers and special-wiring applications (for example, solderless wrapped or wire-clip type connections or shielded conductors) conductors not smaller than No. 30 shall be permitted.

(c) The continuous current carried by conductors shall not exceed the values given in Table 200-B.

200-5. Machine Tool Wire Type MTW. Type MTW wire shall conform to the following construction:

(a) Annealed stranded copper wire with construction for non-flexing and flexing service in accordance with Table 200-A.

(b) Flame-retardant, moisture, heat, and oil resistant thermoplastic insulation suitable for use at maximum operating temperatures of 90°C. in dry locations and 60°C. where exposed to moisture, oil, or coolants.

(c) Insulation thickness in accordance with Table 200-A.

Exception: Wire Nos. 14-10 with 45 mils insulation and Wire No. 8 with 60 mils insulation shall be permitted.

NOTE: As defined in the National Electrical Code, Type MTW Wire having a nominal thickness indicated in Column A consists of a conductor and thermoplastic insulation. Type MTW Wire in Column B consists of a conductor and thermoplastic insulation having a nominal thickness indicated in Column B, and covered with a nylon or thermoplastic polyester jacket.

(d) A durable surface marking of "MTW", and where the conductor stranding is that shown as flexing in Table 200-A, "Flexing" or "Class K."

CHAPTER 210. WIRING METHODS AND PRACTICES

210-1. General Requirements.

(a) Conductors shall be identified at each termination to correspond with the identification on the diagrams and shall be color coded as follows:

Black — Line, load, and control circuits at line voltage.

Red — AC control circuits, at less than line voltage.

Blue — DC control circuits.

Yellow — Interlock control circuits supplied from an external power source.

Green (with or without one or more yellow stripes) — Equipment grounding conductor where insulated or covered.

White — Grounded circuit conductor.

Exception No. 1. Internal wiring on individual devices purchased completely wired.

Exception No. 2. Where insulation is used that is not available in the colors required.

Exception No. 3. Where multiconductor cable is used.

Exception No. 4. Conductors used to connect electronic, precision, static, or similar devices or panels.

Exception No. 5. Where local conditions require that the control circuit be grounded, it shall be sufficient to use a green (with or without one or more yellow stripes) or a bare conductor from the transformer terminal to a grounding terminal on the control panel.

(b) Conductors and cables shall be run without splices from terminal to terminal.

Exception: Splices shall be permitted to leads attached to electrical equipment, such as motors and solenoids, and shall be insulated with oil-resistant electrical tape.

(c) Terminals on terminal blocks shall be plainly identified to correspond with markings on the diagrams.

(d) Shielded conductors shall be so terminated to prevent fraying of strands and to permit easy disconnection.

210-3. Panel Wiring.

(a) Panel conductors shall be supported where necessary to keep them in place. Wiring channels shall be permitted where made of a flame-retardant insulating material.

(b) Where back connected control panels are used, access doors or swingout panels which swing about a vertical axis shall be provided.

(c) Multiple-device control panels shall be equipped with terminal blocks or with attachment plugs and receptacles for all outgoing control conductors.

210-5. Machine Wiring.

(a) Conductors and their connections external to the control panel enclosure shall be totally enclosed in suitable raceways or enclosures as described in Chapter 220, unless otherwise permitted in this Section.

(b) Fittings used with raceways or multiconductor cable shall be liquidtight.

(c) Liquidtight flexible metal conduit or multiconductor cable shall be used where necessary to employ flexible connections to pendant pushbutton stations. The weight of pendant stations shall be supported by chains or wire rope external to the flexible conduit or multiconductor cable.

(d) Liquidtight flexible metal conduit or multiconductor cable shall be used for connections involving small or infrequent movements. They shall also be permitted to complete the connection to normally stationary motors, limit switches, and other externally mounted devices.

(e) Connections to frequently moving parts shall be made with conductors for flexing service as shown in Table 200-A in liquid-tight flexible metallic or nonmetallic conduit or multiconductor cable. Flexible cable and conduit shall have vertical connections and shall have sufficient slack to avoid sharp flexing and straining.

Exception: Horizontal connections shall be permitted where the flexible cable or conduit is adequately supported.

(f) Where flexible conduit or cable is adjacent to moving parts, the construction and the supporting means shall prevent damage to the flexible conduit or cable under all conditions of operation.

(g) All conductors of any AC circuit shall be contained in the same raceway.

(h) Conductors connected in AC circuits and conductors connected in DC circuits shall be permitted in the same raceway regardless of voltage, provided they are all insulated for the maximum voltage of any conductor in the raceway.

(i) Connection through a polarized grounding-type attachment plug and receptacle shall be permitted where equipment is removable. The male plug shall be connected to the load circuit.

(j) Where construction is such that wiring must be disconnected for shipment, terminal blocks in an accessible enclosure or attachment plugs and receptacles shall be provided at the sectional points.

CHAPTER 220. RACEWAYS, JUNCTION AND PULL BOXES

NOTE: Raceways and junction boxes are provided for mechanical protection only. See Chapter 240 for acceptable means of equipment grounding.

220-1. General Requirements.

(a) All sharp edges, flash, burrs, rough surfaces, or threads with which the insulation of the conductors may come in contact shall be removed from raceways and fittings. Where necessary, additional protection consisting of a flame-retardant, oil-resistant insulating material, shall be provided to protect conductor insulation.

(b) Drain holes of $\frac{1}{4}$ inch shall be permitted in raceways, junction boxes, and pull boxes subject to accumulations of oil or moisture.

220-3. Per Cent Fill of Raceways. The combined cross-sectional area of all conductors and cables shall not exceed 50 per cent of the interior cross-sectional area of the raceway. The fill provisions shall be based on the actual dimensions of the conductors and/or cables used.

220-5. Rigid Metal Conduit and Fittings.

(a) Rigid metal conduit and fittings shall be of galvanized steel, meeting the requirements of ANSI Standards C80.1-1966 (R1971) and C80.4-1963 (R1974), or of a corrosion-resistant material suitable for the conditions.

(b) Conduit smaller than $\frac{1}{2}$ inch, electrical trade size, shall not be used.

(c) Fittings shall be threaded unless structural difficulties prevent assembly.

(d) Running threads shall not be used.

(e) Conduit shall be securely held in place and supported at each end.

(f) Where conduit enters a box or enclosure, a bushing or fitting providing a smoothly rounded insulating surface shall be installed to protect the conductors from abrasion, unless the design

of the box or enclosure is such as to afford equivalent protection. Where conduit bushings are constructed wholly of insulating material, a locknut shall be provided both inside and outside the enclosure to which the conduit is attached.

(g) Bends of conduit shall be so made that the conduit will not be injured, and that the internal diameter of the conduit will not be effectively reduced. The radius of the curve of the inner edge of any field bend shall not be less than shown in Table 220-A.

Table 220-A
Minimum Radii of Conduit Bends

Size of Conduit, Inches	Minimum Radius of Conduit Bends, Inches
$\frac{1}{2}$	4
$\frac{3}{4}$	4 $\frac{1}{2}$
1	5 $\frac{3}{4}$
1 $\frac{1}{4}$	7 $\frac{1}{4}$
1 $\frac{1}{2}$	8 $\frac{3}{4}$
2	9 $\frac{1}{2}$
2 $\frac{1}{2}$	10 $\frac{1}{2}$
3	13
3 $\frac{1}{2}$	15
4	16
4 $\frac{1}{2}$	20
5	24
6	30

(h) A run of conduit shall not contain more than the equivalent of 4 quarter bends (360 degrees, total).

220-6. Intermediate Metal Conduit. Intermediate metal (steel) conduit shall be permitted and shall be installed in conformance with the provisions of Sections 220-5(b) through 220-5(h).

220-7. Liquidtight Flexible Metal Conduit and Fittings.

(a) Liquidtight flexible metal conduit shall consist of an oil-resistant, liquidtight jacket or lining in combination with flexible metal reinforcing tubing.

(b) Fittings shall be of metal and shall be designed for use with liquidtight flexible metal conduit.

(c) Liquidtight flexible metal conduit smaller than $\frac{1}{2}$ inch, electrical trade size, shall not be used.